



SKU: 0101-0078

Category:

LET Power Supply Unit (L-PSU)

The Tellabs 1000 LET Power Supply Unit (L-PSU) plug-in card converts the -48 V local exchange battery input into 35 V and -32 V required by the common control equipment and line cards in the Tellabs 1000 MSA series Local Exchange Terminal (LET). The L-PSU uses a DC-to-DC switching converter for high efficiency and low thermal dissipation. Only one L-PSU is required to power each Tellabs 1000 MSAP Series LET shelf, however, a card slot is provided for a redundant L-PSU. The L-PSU features two GMT fuses for redundant source coordination. The first fuse protects the DC-DC converter and the second fuse protects the -48 V DC output.

Features

- High-efficiency switching DC-DC converter
- Reverse input polarity protection
- Output over-voltage and over-current shutdown
- Low output voltage alarm
- Low thermal dissipation

Highlights

High Reliability

Only one L-PSU is required to power an RST shelf; however, a card slot is provided for an additional redundant R-PSU. And the R-PSU features input fusing for redundant source coordination

Efficient Power

The L-PSU uses a DC-to-DC switching converter for high-efficiency power generation in a compact form factor.

Low Thermal

The L-PSU uses a DC-to-DC switching converter for high efficiency and low thermal dissipation to minimize the impact on the surroundings.

Specifications

Physical

- Height: 5.125 in (13.018 cm)
- Width: 1.0 in (2.54 cm)
- Depth: 10.5 in (26.67 cm)
- Weight: 1.0 lb (0.45 kg)

Power

- The L-PSU features two GMT fuses for redundant source coordination
- The first fuse protects the DC-DC converter
- The second fuse protects the -48 V DC output

Alarm / Monitor / Test

- The unit also provides alarm and status indications to the CPU.
- Test jacks on the front panel can be used to monitor the system voltages.

Environmental

- Temperature: -40° to +149° F (-40° to +65° C)
- Relative Humidity: 5-95% non-condensing
- Altitude: Up to 10,000 feet

Compliance

- GR-1089-CORE

General

- DC-DC Converter Input: -40 V DC to -56.5 V DC
- DC-DC Converter Output: +5.15 V DC \pm 1.5%, -5.15 V DC \pm 10.0%, -32.0 V DC \pm 10%, -39 V DC

to -56.5 V DC

- Low voltage disconnect: -38 V DC
- Output Regulation: 3 5.15 V DC, < 1.5% load, < 1.5% line, < 0.20% per specified temp range
- Ripple and Noise: 3 5 V DC, 1.0% peak-to-peak, -32 V DC @ 100 mV peak-to-peak
- Output Current: +5 V DC 15 A, -5 V DC 2 A, -32 V DC 3 A, -48 V DC, 2 A
- Total available output power: 150 W
- Isolation internal converter: 500 V input to output
- Isolation output ground: Referenced to positive battery input

LED Indicators

- ACTV (green)
- FUSE (red)
- FAIL (red)

Management

- Craft User Interface (CUI)
- Tellabs Panorama Element Management System (EMS)

Software Support

- Minimum base software FP16 and higher

Installations

- Supported in Tellabs 1000 CBA

Ordering Information

- L-PSU: 0101-0078